

General

| Length (mm) | 110 |
|-------------------------------|---|
| Diameter (mm) | 80 |
| Cover | 8mm step tempered glass, Stainless steel (SUS316), |
| Housing Color | Silver |
| Housing Material | Aluminum / ABS |
| Diameter Mounting Sleeve (mm) | 68 |
| Length Mounting Sleeve (mm) | 125 |
| Cut-out (mm) | 69 |
| Cable Color | Black |
| Cable Length (cm) | 50 cm |
| Cable Type | H05RN-F3xG0.75 |

Electronics

| Input Voltage | 220 ~ 240V AC |
|-----------------------|---------------|
| Power Consumption (W) | 5.5 |
| Power Supply | Internal |
| Luminous Efficacy | 79 lm/W |

Lighting

| Emission | Direct |
|------------------------------|------------------|
| Optics (°) | 13 (23 optional) |
| Chip Brand | CREE |
| LED Type | COB |
| LED Quantity | 1 |
| Color Range | White |
| Color Temperature (Kelvin) | 3000 K |
| Colour Rendering Index (CRI) | 82 |
| Luminous Flux | 438 lm |
| Light Distributor | Other |
| Light Sharing | Symmetric |

Control

| Number of Channels | 1 | |
|--------------------|---|--|

Environmental

| Storage Temperature | -20 ~ +40 °C |
|-----------------------|--------------|
| Operating Temperature | -20 ~ +40 °C |
| Impact Protection | IKO8 |
| Ingress Protection | IP67 |



CE ROHS IP67 2 year warranty

Disclaimer

Due to the technical evolution and improvement of our products, the data provided in this document may be updated on a regular basis, and as such, confirmation of this information is strongly recommended prior to the order process. OneEightyOne is not responsible for any discrepancies in this document following changes in our products. We reserve the right to make technical changes to our products and to change information, at its sole discretion, without notice.



oneeighty one.com



SPECIALISTS IN CREATIVE LED LIGHTING

Installation Instruction

Model: 34605

Input: AC220-240V

Power: 1x5W

CE







Safety Notice:

Please read the installation instruction before installing the inground. The installation should be done by a professional. Failure to comply with the instruction may result in damage, fire or personal injury.

- 1. While using the products please pay attention to the input voltage.
- 2. Please use our local standard identification cable. Pay attention that it must be higher than the input voltage and constant current of the product.
- 3. Please turn off the power before installing, repairing or replacing the ingroud.
- 4. If parts need to be replaced or repaired, please use the specified parts from the supplier. The changes should be applied by a professional.













