

General

Product Type	Converter
Wire Strip Length	5mm
Wire Type	2.5mm2

Electronics

Power Supply	N/A
LED Outputs	3

Control

Output Signal	0~10V
Control	PWM
Dimming Range	0~100%

Protection

Reverse Polarity	Yes
LED Output Short	Yes
Overload	Yes

Environmental

Operating Temperature	-30 ~ +55 °C
Ingress Protection	IP44

C € F© IP44 5_{warranty}

Disclaimer

Due to the technical evolution and improvement of our products, the data provided in this document may be updated on a regular basis, and as such, confirmation of this information is strongly recommended prior to the order process. OneEightyOne is not responsible for any discrepancies in this document following changes in our products. We reserve the right to make technical changes to our products and to change information, at its sole discretion, without notice.

181

oneeighty one.com

LT-3060-010V LED Dimming Signal Converter



LT-3060-010V is a high performance dimming signal convertor, to convert PWM dimming signal to 0-10V analog dimming signal. By using this product, one dimming control system could control multiple drivers or LED lamps in different dimming signal.

1. Product Parameter:

LT-3060-010V

Signal Input: PWM ×3CH

(Compatible with CV/CC Power PWM

and Signal PWM)

Working Voltage: 12~24V DC

Signal Output: 0~10V x 3CH (Default)

PWM (0~10V) x3CH

Dimming Range: 0~100%

Working Temperature: -30°C~55°C

Product Size: L121×W39×H39(mm)

L123×W42×H42(mm)

Weight(G.W.): 80g

Package Size:

2. Conjunction Diagram:

