LED Dimmer Touch DIM - D1



2252100 General Product Type Controller Housing Material PC Wire Strip Length 5mm Wire Type 2.5mm2 Electronics Input Voltage 12 ~ 24V DC Output Voltage 12 ~ 24 V DC Output Current (mA) max/output 4000 Output Current Max. (A) 12 Output Power (W) 144W @ 12V, 288W @ 24V Power Supply N/A LED Outputs 3 Lighting Color Range Single Color Control Output Signal PWM-CV Manual Dimming Range 5~100% ı Number of Channels 3 Functions programmable Protection **Reverse** Polarity Yes LED Output Short Yes Overload Yes

Environmental

Restart after Protection

Control

Zones

Operating Temperature	-30 ~ +55 °C
Ingress Protection	IP20

18

Yes

CE FC IP20 5^{year}

Disclaimer

Due to the technical evolution and improvement of our products, the data provided in this document may be updated on a regular basis, and as such, confirmation of this information is strongly recommended prior to the order process. OneEightyOne is not responsible for any discrepancies in this document following changes in our products. We reserve the right to make technical changes to our products and to change information, at its sole discretion, without notice.

OneEightyOne Valschermkade 27 - 28 | 1059CD | Amsterdam +31 20 8200170 | info@oneeightyone.com | www.oneeightyone.com oneeighty

one.com

LTECH

D1 Dimming Touch Panel

L86×W86×H36(mm)

L113×W112×H50(mm)

Series Touch Panel



FC CE PROHS (warranty) (S years)

1. Technical Specs:

- Input Voltage:
- Load Current:
- Dimming Range: 5
- Max Output Power: 144W/288W(12V/24V)

12-24Vdc

4Ax3CH Max 12A

2. Installation Instruction:



5%-100% 144W/288W(12V/24V)

Uninstall


3. Product Size:

Dimensions-

Package Size:

Weight(G.W.):

Working Temp.: -30°C~55°C



208g

LTECH

4. Key Functions:





